




## Models

Colour

☐ White

Ref:

63731-124703



## Technical Details

Maximum Power:	150-360 W
Voltage:	220-240V AC
Multi-Voltage:	100-240V AC
Frequency:	50-60 Hz
Max Output Current:	1.5 A
Dimmable:	1-10 V
Use:	Indoor
IP Protection:	IP20
Material:	PC

Size:	52x52x25 mm
Height:	52 mm
Width:	52 mm
Length:	25 mm
Total Weight:	0.06 kg
Detection Distance:	30 m
Working Temperature:	-30°C ~ +55°C
Warranty:	3 Years
Certifications:	CE & RoHS, UKCA



## Description

The **RF 1-10V Universal LED Dimmer/Push button** uses wireless technology in **the 2.4 GHz band**. It is specially developed for the control of **1-10V dimmable LED lamps** without the need to install wiring.

Thanks to this dimmer, it is possible to manually change the luminosity of the luminaires, creating various environments for different occasions and needs.

This dimmer can have several control places, either wireless or classic buttons connected by cable.

### Characteristics RF 1-10V Universal LED Dimmer/Push button

The RF 1-10V Universal LED Dimmer/Push button can be mounted anywhere thanks to its extra-flat design, behind the switch or inside the junction box, as it is only 25 mm thick.

The **controller can be used with the RF Remote for 1-10V and Triac Controllers, the LED 1-10V and Triac Universal Dimmer Switch** as well as classic pushbuttons.

### Operation of the RF 1-10V Universal LED Dimmer/Push button

The use of the **RF 1-10V Universal LED Dimmer** is very simple. To turn the luminaires on and off, you only have to press the button briefly and, when you want to regulate the intensity of the luminaire, you have to keep the button pressed until you reach the desired intensity. The dimmer has a memory for storing the brightness at which the luminaire has been switched off.

Don't miss this opportunity, and take advantage of it to enjoy the best quality lighting, accompanied by elegance and style.



## Additional photographs

