



## Models

Power

Ref:

3 W

65439-130879



## Technical Details

<b>Tension</b>	220-240V AC
<b>Frequency</b>	50-60 Hz
<b>Electric Insulation Class</b>	II
<b>Adjustable</b>	No
<b>Light Source</b>	SMD5730
<b>LED number</b>	30
<b>Light color</b>	Cool White
<b>Color Temperature</b>	6000K - 6500K
<b>Brightness</b>	200 lm
<b>Emergency Lighting</b>	Permanent - Non-Permanent
<b>Use</b>	Outdoor
<b>IP Protection</b>	IP65
<b>Material</b>	ABS
<b>Installation</b>	Surface

<b>High</b>	70 mm
<b>Wide</b>	350 mm
<b>Lenght</b>	120 mm
<b>Room Temperature Work</b>	0 °C~+40 °C
<b>It works with battery</b>	Yes
<b>Battery type</b>	Ni-Cd
<b>Number of Batteries</b>	1
<b>Battery Voltage</b>	3.6 V
<b>Battery Capacity</b>	1000 mAh
<b>Useful life</b>	40,000 Hours
<b>Contains battery</b>	Yes
<b>Autonomía Máxima</b>	3 h
<b>Power</b>	3 W
<b>Energy Efficiency 2023 (EU-2019/2015)</b>	F



## Description

**The LED emergency light features watertight housing, an IP65 protection factor, it provides high resistance to external weather factors** and is ideal for indoors and outdoors. It includes protection fuses and a battery with an autonomy of up to 3 hours. The LEDs give this luminaire great energy savings as well as excellent performance.

The LED emergency light allows both permanent and non-permanent lighting. This emergency light is pre-assembled as a non-permanent light. By modifying the position of the PCB connector you can select the operation mode of this emergency light.

The **AutoTest** emergency luminaires not only meet the basic requirements of standard emergency lighting products, but also **include the AutoTest automatic self-test system**. AutoTest products only require visual inspection as the integral luminaire status LED informs the operational status of the luminaire and the type of fault, should a failure have occurred.

The 3W LED emergency light is **the most practical, economical and simple solution in the event of any occurrence, such as a possible power cut**. It is easy to installed either on the wall and on the ceiling, thanks to its recessed mounting.

\*It has an LED operation indicator.

\*For correct operation as emergency lighting must connect the pre-wired battery.



## Additional photographs

