



Models

| | |
|-----------------|--------------|
| Combination | Ref: |
| Light + 5 Signs | 65528-131012 |



Technical Details

| | | | |
|---|------------------|-----------------------------|-----------------|
| Power: | 2 W | Installation: | Surface |
| Voltage: | 220-240V AC | Size: | 350x210x40 mm |
| Frequency: | 50-60 Hz | Working Temperature: | 0 °C ~ +40 °C |
| Energy Efficiency 2021 (UE-1369/2017): | A | Battery: | AAA - NiMH |
| Energy Efficiency 2023 (UE-2019/2015): | F | Number of Batteries: | 1 |
| Emergency Lighting: | Permanent | Battery Voltage: | 3.6 V |
| Use: | Indoor | Battery Capacity: | 600 mAh |
| IP Protection: | IP20 | Warranty: | 3 Years |
| Material: | Methacrylate, PC | Certifications: | CE & RoHS, UKCA |



Description

This Double Sided Emergency LED Sign Kit with Autotest Button allows us to practically and effectively signal exits, directions and the location of restrooms.

It uses a 3.6V 800mAh Ni-Cd battery with 3h of battery life. This **Double Sided Emergency LED Sign Kit with Autotest Button features a light support with LEDs offering high energy savings and excellent properties.**

Its innovative design allows us to install it in four ways; suspended, recessed, side-ways and upright. This kit includes 5 posters (exit, right signal, left signal, forward signal, downward signal and WC).

AutoTest emergency luminaires not only meet the basic requirements of standard emergency lighting products but also include the **AutoTest automatic self-test system**. The AutoTest products only require visual inspection as the integral luminaire status LED informs the operational status of the luminaire and the type of fault, should a failure have occurred.

Without a doubt, this Emergency LED Sign Kit available here at LEDKIA **is a key element in any emergency lighting system.**

* Includes test button to check the operation of the unit.

* Permanent lighting.



Additional photographs

