



## Models

Finish

☐ PC

Ref:

6540-15268

## Technical Details

<b>Power:</b>	1.5 W
<b>Maximum Power:</b>	800 W
<b>Voltage:</b>	220-240V AC
<b>Multi-Voltage:</b>	100-277V AC
<b>Frequency:</b>	50-60 Hz
<b>Dimmable:</b>	1-10 V
<b>Use:</b>	Indoor, Outdoor
<b>IP Protection:</b>	IP65

<b>Material:</b>	PC
<b>Detection Distance:</b>	15 m
<b>Detection Angle:</b>	150°-360°
<b>Working Temperature:</b>	-35°C~+70°C
<b>Warranty:</b>	3 Years
<b>Certifications:</b>	CE & RoHS, UKCA
<b>Brand:</b>	MERRYTEK



## Description

Motion Detector for 60W Trunking LED Linear Bar. When installed at a height of 15m its detection area is 15 square metres. It supports a maximum load of 800W in multi-voltage. Detection Area: 50% or 100% detection area. With the Merritek MH10 controller you can control **functions such as:**

Detection Area: Detection Area 50% or 100%.

Hold time: Time it stays on after detecting a movement. 5s ~ 30min.

Stand-by Period: Time that elapses between the luminaire entering Stand-by mode and the luminaire switching off completely.

Stand-by DIM Level: Illumination level in Stand-by mode. After detecting motion, this mode is entered.

Daylight Sensor: Minimum amount of light required for the luminaire to switch on. It can detect that night (5 Lux) or dusk (100-200 Lux) has arrived.

\*End cap not included.



## Additional photographs

