





Models

Technical Details

| Tension | 220-240V AC |
|---|-------------|
| Rated Voltage | 85-265V AC |
| Frequency | 50-60 Hz |
| Casquillo | Т8 |
| Light Source | SMD3014 |
| Energy Efficiency 2023 (EU- 2019/2015) | F |
| Use | Indoor |
| IP Protection | IP44 |

| Material | Aluminum, Pc |
|--------------------------|---------------|
| Lenght | 1500 mm |
| Diameter | 26 mm |
| Detector | PIR |
| Detection Angle | 180° |
| Room Temperature Work | -20 °C~+45 °C |
| Tube Length | 150 cm |
| Selectable Opening Angle | 160 |





Description

This 24W T8 LED Tube has PIR motion detection, emits a brightness of 2,400 lumens, has a 30,000 hour lifespan and comes in a translucent cover.

The detector senses invisible infrared emissions coming from either people or heat sources without emitting any radiation, activating only when a heat source moves in front of the switch and then, after 30 or 40 seconds, reducing brightness by 20% once the heat source is no longer in range.

For the tubes to function correctly, we recommend that they be installed in open luminaires

The 85V-265V AC Multi-Voltage refers to peaks and drops. The tubes cannot continuously function at these voltages.

How to install LED Tubes





Additional photographs

